

# **Terrameter VES**

1D Resistivity and IP

EVEN BASIC METHODS DESERVE MORE THAN BASIC INSTRUMENTS

# **Technical Specification**

Inspired by the ABEM Terrameter LS 2, the **ABEM**Terrameter VES brings new levels of performance and functionality to your VES surveys for resistivity and IP.

#### General

30% better resolution\*

50% higher maximum current\*

More memory\*

Remote control and diagnostics

**Built-in GNSS (GPS & GLONASS)** 

Real-time sounding curve

Better connectivity with Wi-Fi, Ethernet and USB\*

User-friendly interface with ABEM Active Guidance



# **Upgrades**

The Terrameter VES can be upgraded to the VES MAX specification and both instruments can be upgraded to full imaging systems - simply choose the Terrameter LS 2 model that suits your needs.



## **Accessories**

A range of quality accessories are available for the VES instruments including VES cable sets, non-polarising electrodes, flight cases, power adapters and batteries, plus the plug-and-play Terrameter Log borehole resistivity logging tool.








## The VES Survey Method

VES (vertical electrical sounding) is a basic method which uses four electrodes, two to inject current (C1 & C2) and two to measure voltage (P1 & P2). When the electrodes are moved apart, the electrical field extends deeper into the ground, allowing deeper measurements. Raw data are processed with inversion software to provide a model of resistivity versus depth beneath the centre of the electrode spread.



VES is an excellent, easy-to-use method for identifying aquifers, saline intrusion, geological layering, large mineral bodies, and for predicting the earthing properties of the ground around electrical installations, especially DC (direct current) sites where a deeper assessment is often required.

TRANSMITTER	Terrameter VES	Terrameter VES MAX
Output power (W)	100	250
Output voltage (V)	400	600
Output current (mA)	1500	2500
Constant current	Y	es
Precision (%)		0.1
Accuracy (%)		0.2

#### **RECEIVER**

Measure modes	Resistivity,	IP (50% duty cycle), SP		
Induced polarization 100 % duty cycle mode	No	Yes		
Full waveform	No	Yes		
Number of measuring channels	1,3	(2		
All channels galvanically isolated	n/a	Yes		
Voltage ranges	1(±15V)	3 (±2.5V, ±15V, ±600V)		
Input impedance (MOhm)	30	Up to 200		
Precision (%)		0.1		
Accuracy (%)		0.2		
A/D converter (bits)		24		
Theoretical resolution (nV)	22.5	HIGH VOLTAGE!		
On-screen sounding curve	Yes	Yes		
Multi-electrode switching	No	Yes – up to 16 electrodes		
CENEDAL				

#### **GENERAL**

Memory	32GB (			
Built-in GNSS	SD GPS & GLONASS			
Connectivity	USB, Wi-Fi, Ethernet			
Display	8.4" full colour display 39x32x21cm			
Internal battery		Option		Yes
Office power supply		Option		Yes
User remote control			Yes	
Remote diagnostic support			Yes	
Case		Wooden ABEM crate	9	Peli-style flight case
Environmental	IEC IP66 -20 to +70°C			

#### **DESIGN & DIMENSIONS**

Case design	Aluminium alloy 39x32x21cm		
Weight	9.2 kg	10.6 kg	
	(without internal battery)	(with internal battery)	

#### **ABEM Terrameter VES MAX**

The ABEM Terrameter VES MAX is a 'bridging' instrument for resistivity and IP, aimed at those with serious aspirations to start doing ERT in the future, and those with the budget for a fully-specified VES instrument, capable of advanced functionality. It should be of particular interest to those with requirements for IP or deeper resistivity surveys as it provides more power and improved sensitivity over the regular ABEM Terrameter VES.



### Visit us at: www.guidelinegeo.com

**GUIDELINEGEO**